



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE1632 Integrated Circuit Vertical/Horizontal Sync Separator

Description:

The NTE1632 separates the horizontal and vertical sync pulses from the composite TV video signal and uses them to synchronize vertical and horizontal oscillators. The NTE1632 is supplied in a 18-Lead DIP type package.

Features:

- Horizontal sync separator & noise inverter
- Horizontal oscillator
- Horizontal phase detector (sync to oscillator)
- Horizontal output stage
- Inhibit of horizontal phase detector & video transmitter identification circuit during vertical oscillator flyback
- Stabilizer & supply circuit for starting the horizontal oscillator & output stage directly from the mains rectifier
- Duty factor of horizontal output pulse is 50% when flyback pulse is absent
- Vertical sync separator
- Vertical comparator with internal 3% precorrection circuit for vertical oscillator/sawtooth generator
- Vertical driver stage
- Vertical blanking pulse generator with external adjustment of pulse duration (50Hz: 21 lines: 60Hz: 17 lines)
- Vertical guard circuit
- Bandgap 6.5V reference voltage for vertical oscillator & comparator
- Synchronized vertical oscillator/sawtooth generator (synchronization inhibited when no video transmitter is detected)
- Time constant switch for phase detector (fast time constant during catching)
- Slow time constant for noise only conditions
- Time constant externally switchable (e.g. fast for VCR)
- Second phase detector for storage compensation of horizontal deflection stage
- Sandcastle pulse generator (3 levels)
- Video transmitter identification circuit
- Internal circuit for 3% parabolic precorrection of the oscillator/sawtooth generator. Comparator supplied with precorrected sawtooth & external feedback input

| Parameter | Symbol | Min | Typ | Max | Unit |
|---|-----------------|-----|-----|-----|------|
| Supply: | | | | | |
| Minimum Current Required to Start Horizontal Oscillator & Output Stage (Pin 16) | I ₁₆ | - | >4 | - | mA |

| Parameter | Symbol | Min | Typ | Max | Unit |
|---|------------------|-------------------|-----------|------|--------------------------|
| Main Supply Voltage (Pin 10) | $V_P = V_{10-9}$ | - | 12 | - | V |
| Supply Current | $I_P = I_{10}$ | - | 55 | - | mA |
| Input Signals: | | | | | |
| Sync Pulse Input Voltage (Peak-to-Peak Value; Negative Going) | $V_{5-9(p-p)}$ | 0.15 to 1V | | | |
| Output Signals: | | | | | |
| Horizontal Output Pulse (Open Collector) at $I_{11} = 40\text{mA}$ | V_{11-9} | - | <0.5 | - | V |
| Vertical Output Pulse (Emitter-Follower) at $I_1 = 10\text{mA}$ | V_{1-9} | - | >4 | - | V |
| Ratings: | | | | | |
| Start Current (Pin 16) | I_{16} | - | - | 8 | mA |
| Supply Voltage (Pin 10) | $V_P = V_{10-9}$ | - | - | 13.2 | V |
| Total Power Dissipation | T_{tot} | - | - | 1.1 | W |
| Storage Temperature Range | T_{stg} | -55 to +150°C | | | |
| Operating Ambient Temperature Range | T_{amb} | -25 to +65°C | | | |
| Thermal Resistance: | | | | | |
| From Junction to Ambient in Free Air | $R_{th J-A}$ | - | 50 | - | kW |
| Characteristics: $I_{16} = 5\text{mA}$; $V_P = 12\text{V}$; $T_{amb} = 25^\circ\text{C}$ (unless otherwise indicated) | | | | | |
| Supply: | | | | | |
| Supply Current at Pin 16 | I_{16} | 4 to 8 | | | mA |
| Stabilized Supply Voltage (Pin 16) | V_{16-9} | - | 8.7 | - | V |
| Supply Current (Pin 10) | I_{10} | - | 55 | - | mA |
| | | - | <70 | - | mA |
| Supply Voltage (Pin 10) | $V_P = V_{10-9}$ | - | 12 | - | V |
| | | 10 to 13.2 | | | V |
| Video Input (Pin 5): | | | | | |
| Top-Sync Level | V_{5-9} | - | 3.1 | - | V |
| | | 1.5 to 3.75 | | | V |
| Sync Pulse Amplitude (Peak-to-Peak Value) (Note 1) | $V_{5-9(p-p)}$ | - | 0.6 | - | V |
| | | 0.15 to 1 | | | V |
| Slicing Level | - | - | 50 | - | % |
| | | 35 to 65 | | | % |
| Delay Between Video Input & Detector Output | t_1 | - | 0.35 | - | μs |
| Noise Gate (Pin 5): | | | | | |
| Switching Level | V_{5-9} | - | 0.7 | - | V |
| | | - | <1 | - | V |
| First Control Loop (Sync to Oscillator: Pin 8) | | | | | |
| Holding Range | Δf | - | ± 800 | - | Hz |
| Catching Range | Δf | ± 600 to 1100 | | | Hz |
| Control Sensitivity Video with Respect to Oscillator, Burst Key & Fly-back Pulse (For Slow Time Constant) (For Fast Time Constant) | - | - | 1 | - | $\text{kHz}/\mu\text{s}$ |
| | | - | 275 | - | $\text{kHz}/\mu\text{s}$ |

| Parameter | Symbol | Min | Typ | Max | Unit |
|---|---------------------------|-------------------|---------------|--------|-----------------|
| Second Control Loop: (Horizontal Output to Flyback: Pin 14) | | | | | |
| Control Sensitivity; Static (Note 2) | $\Delta t_d / \Delta t_o$ | - | 400 | - | $\mu s / \mu s$ |
| Control Range | t_d | 1 to 50 | | | μs |
| Controlled Edge | Negative | | | | |
| Phase Adjustment (Via 2nd Control Loop; Pin 14) | | | | | |
| Control Sensitivity | | - | 25 | - | $\mu A / \mu s$ |
| Maximum Permissible Control Current | $\pm I_{14}$ | - | <50 | - | μA |
| Horizontal Oscillator (Pin 15): | | | | | |
| Frequency (No Sync) | f_{OSC} | - | 15625 | - | Hz |
| Frequency Spread ($C_{OSC} = 2.2nF$; $R_{OSC} = 40k\Omega$) | Δf_{OSC} | - | <4 | - | % |
| Frequency Deviation Between Starting Point of Output Signal & Stabilized Condition | Δf_{OSC} | - | 6 <8 | - | % |
| Temperature Coefficient | TC | - | 1.10 -4k-1 | - | - |
| Horizontal Output (Pin 11) | | | | | |
| Output Voltage; High Level | V_{11-9} | - | <13.2 | - | V |
| Voltage at which Protection Starts | V_{11-9} | - | 0.3 | - | V |
| | | - | 0.5 | - | |
| Output Voltage; Low Level Start Condition at $I_{11} = 10mA$ Normal Condition at $I_{11} = 40mA$ | V_{11-9} | - | 0.3 | - | V |
| | | - | 0.5 | - | |
| Duty Factor of Output Signal During Starting (No phase shift; voltage at pin 11 low) | - | - | 65 | - | % |
| Duty Factor of Output Signal without Flyback Pulse | - | - | 50 | - | % |
| | | 45 to 55 | | | % |
| Controlled Edge | Negative | | | | μs |
| Duration of Output Pulse (Fig 3) | | $t_d + t_o + 2.5$ | | | |
| Sandcastle Output Pulse (Pin 17): | | | | | |
| Output Voltage During: Burst Key | V_{18-9} | - | >10 | - | V |
| Horizontal Blanking | V_{17-9} | - | 4.6 | - | V |
| | | 4.2 to 5 | | | |
| Vertical Blanking | V_{17-9} | - | 2.5 | - | V |
| | | 2 to 3 | | | |
| Pulse Duration Burst Key | t_p | - | 4 | - | μs |
| Horizontal Blanking | Flyback Pulse (note 3) | - | - | - | - |
| Vertical Blanking for 50Hz application ($-I_{12}$: 0 to 0.1mA) for 60Hz application ($-I_{12}$: typ -0.2mA) | - | - | 21 17 | -lines | |
| Delay Between the Start of the Sync at the Video Input & the Rising Edge of the Burst Key Pulse | t_2 | - | 4.9 | - | μs |
| | | 4.5 to 5.3 | | | |

| Parameter | Symbol | Min | Typ | Max | Unit |
|--|------------------|---------------|---------------|-----|---------------|
| Coincidence Detector: Video Transmitter ID Circuit; Time Constant Switches (Pin 18) (See Fig 2) | | | | | |
| Detector Output Current | $\pm I_{18}$ | - | 300 | - | μA |
| Voltage During Noise (Note 4) | V_{18-9} | - | 0.3 | - | V |
| Voltage Level for In-Sync Condition | V_{18-9} | - | 7.5 | - | V |
| Switching Level Slow to Fast | V_{18-9} | - | 3.5 | - | V |
| | | 3.2 to 3.8 | | | |
| Switching Level Must Function Active; ϕ_1 Fast to Slow | $V_{\pm 8-9}$ | - | 1.2 | - | V |
| | | 1.0 to 1.4 | | | |
| Vertical Period Counter 3 periods fast | V_{18-9} | - | 0.12 | - | V |
| | | 0.08 to 0.16 | | | |
| Switching Level Slow to Fast (Locking) Mute Function Inactive | V_{18-9} | - | 1.7 | - | V |
| | | 1.5 to 1.9 | | | |
| Switching Level Fast to Slow (Locking) | V_{18-9} | - | 5.0 | - | V |
| | | 4.7 to 5.3 | | | |
| Switching Level for VCR (Fast Time Constant) Without Mute Function | V_{18-9} | - | 8.6 | - | V |
| | | 8.2 to 9.0 | | | |
| Video Transmitter ID Output (Pin 13) | | | | | |
| Output Voltage Active (No Sync) at $I_{13} = 1\text{mA}$ | V_{13-9} | - | >10 | - | V |
| | | - | 11 | - | |
| Output Voltage Active (No Sync) at $I_{13} = 5\text{mA}$ | V_{13-9} | - | >7 | - | V |
| Output Voltage Inactive | V_{13-9} | - | <0.5 | - | V |
| | | - | 0.1 | - | |
| VCR Switching (Pin 13): | | | | | |
| Input Current for Fast Time Constant Phase Detector ϕ_1 , with Mute Function Active | I_{13} | - | 0.6 | - | mA |
| | | 0.4 to 0.8 | | | |
| Input Pulse Amplitude (Peak-to-Peak Value) | $V_{12-9 (p-p)}$ | - | <12 | - | V |
| Input Resistance | R_{12-9} | - | 2.7 | - | k Ω |
| Delay Time of Sync Pulse (Measured in ϕ_1) | t_o | - | 1.3 | - | μs |
| Duration of Vertical Blanking Pulse (Pin 12) for 50Hz application; 21 lines blanking for 60Hz application; 17 lines blanking | $-I_{12}$ | - | 0.2 | - | mA |
| | | >0.15 to <0.3 | | | |
| | | - | <0.1 | - | |
| Maximum Allowed Input Current | $-I_{12}$ | - | <0.4 | - | mA |
| Vertical Sawtooth Generator (Pin 3): | | | | | |
| Vertical Frequency (No Sync) | f_s | - | 46 | - | Hz |
| Frequency Spread ($C_{osc} = 680\text{nF}$, $R_{osc} = 180\text{k}'$ at >26V) | Δf_s | - | <4 | - | % |
| Synchronization Range | - | - | 22 | - | % |
| Input Current at $V_{3-9} = 6\text{V}$ | I_3 | - | <2 | - | μA |
| Frequency Shift for $V_p = 10$ to 13V | Δf_s | - | <0.2 | - | % |
| Temperature Coefficient | TC | - | 1.10-4k -1 | - | - |
| Comparator (Pin 2): | | | | | |

| Parameter | Symbol | Min | Typ | Max | Unit |
|---|----------------|------------|-----|-----|---------|
| Input Voltage; DC Level | V_{2-9} | - | 4.4 | - | V |
| | | 4.0 to 4.8 | | | |
| AC level (Peak-to-Peak) | $V_{2-9(p-p)}$ | - | 1.6 | - | V |
| Input Current at $V_{2-9} = 6V$ | I_2 | - | <2 | - | μA |
| Sawtooth Internal Precorrection (Parabolic Convex) | - | - | 3 | - | % |
| Vertical Output Stage: Emitter Follower (Pin 1) | | | | | |
| Output Voltage at $I_1 = 10mA$ | V_{1-9} | - | 3.6 | - | V |
| | | 3.2 to 5 | | | |
| Output Current | I_1 | - | <20 | - | mA |
| Vertical Guard Circuit: | | | | | |
| Activating Voltage Levels (Vertical Blanking Level is 2.5V) Switching Level Low | V_{2-9} | - | 3 | - | V |
| Switching Level High | V_{2-9} | - | 5.7 | - | V |
| | | 5.3 to 6.1 | | | |

Note 1 Up to 1V peak-to-Peak the slicing level is constant; at amplitudes exceeding 1V Peak-to-Peak, the slicing level will increase.

Note 2 t_d = delay between negative transient of horizontal output pulse and the rising edge of the flyback pulse. t_o = delay between the rising edge of the flyback pulse and the start of the current in ϕ_1 (pin 8).

Note 3 The duration of the flyback pulse is measured at the input switching level which is about 1V (t_{f1}).

Note 4 Depends on DC level at pin 5; value given applicable for $V_{5-9} \sim 5V$.

