

<u>Function</u>	<u>Range</u>	<u>Resolution</u>	<u>Accuracy</u>
<u>DC Voltage</u>	200mV	100 μ V	$\pm(0.5\% \text{reading} + 3 \text{digits})$
	2V	1mV	
	20V	10mV	
	200V	100mV	
	600V	1V	
<u>AC Voltage</u> <u>(40-450 Hz)</u>	2V	1mV	$\pm(0.5\% \text{reading} + 3 \text{digits})$
	20V	10mV	
	200V	100mV	
	600V	1V	$\pm(0.8\% \text{reading} + 5 \text{digits})$
<u>Resistance</u>	200ohm	10Mohm	$\pm(0.5\% \text{reading} + 3 \text{digits})$
	2Kohm	1ohm	
	20Kohm	10ohm	
	200Kohm	100ohm	
	2Mohm	1Kohm	
	20Mohm	10Kohm	